Gammatech Enhanced E Series

The World's First Rugged Notebook with Terabyte Storage

A unique mobile solution that brings you more flexibility and security and more data storage than ever before.

A rugged notebook that is drop, shock, spill and dust resistant and lets you personalize your computing experience.



Pick a rugged solution that fits your need!

D14E0Maximum Data Capacity


The data capacity is doubled to one terabyte with access to two hard drives in one system so you can enjoy maximum data storage, lightening fast data access and ultimate performance.

D14E1Real Time Back Up

No more worries about loss of data! D14E1 offers you a real time back up. All data is automatically synchronized from the primary drive to the secondary drive so that all data is always completely secure.

D14E2 Ultimate Flexibility

D14E2 brings you the ease of organizing your data. With two separate drives, you can store your professional tasks in one drive and enjoy your personal and entertainment media in the other.







Drop Resistant	Magnesium alloy case - 20 times stronger than ABS plastic, offering higher survival rate after drops and bumps. 26 drops from 76 cm height to plywood over concrete with unit off and display closed. 5 units to pass. Simulate MIL STD 810F, Method 516.4, Procedure IV.	
Shock Resistant	Anti-shock mounting design protects LCD screen and hard dis	sk drive from damage and data loss.
	Flexible HDD cable design absorbs shock from drops.	
	Simulate MIL STD 810F, Method 514.5, Procedure I, Category 10, Fig 16 & 17/ASTM4169, Truck Transport, 11.5.2 Random test, Assurance Level II	
Spill Resistant	Spill resistant keyboard, touchpad and switches.	
	Spill resistant design stops spills from leaking into sensitive int	terior parts.
Dust Resistant	All Input/Output ports	
Optical Disk Lock	Exclusive optical disk tray lock prevents unintentional tray ejec	ct from drop and vibration.
Battery Protection	Double protection smart battery circuitry prevents damage ca Smart Battery Calibration helps fight the loss of battery capaci	
Stylish Rugged	Magnesium alloy top cover with diamond cut rim and 4 concu	
otys.r.r.uggeu		
Processor	Intel® Core™ 2 Duo, FSB 1066 (Montevina Platform)	
Chipset	North Bridge: Intel® GM45	South Bridge: Intel® ICH9M-Enhanced
System Memory	Two 200-pin DDRII SODIMM sockets each for 1GB/2GB (8GB Ma	aximum)
RAID Controller	Intel Mobile Enhanced RAID Controller Support RAID (E0 RAID 0, E1 RAID 1)	
Hard Disk Drive	2.5" 9.5mm SATA II Hard Disk Drive 2x500GB SATA II 5400 RPM HDD	
HAIA DISK DITYE	(E0-7200 RPM, free fall sensor)	
External ODD	External USB 8X Slim Super Multi DVD Write plus DL	
Display	14.1"WXGA (1280x800) TFT, WXGA+ (1440x900)-option	
Graphics & Video	Webcamera: 1.3Megapixel (option)	
	Touch Screen: Optional resistive type touch panel (factory option), optional sunlight readable function	
	Intel® GM45 Integrated graphics	
Audio	Shared system memory up to 1759MB (depanding on RAM and Links Definition Audio stores)	• Two 1.5W speakers
	High Definition Audio, stereo	• Two 1.5W speakers
1/0 0	Internal Microphone One PCMCIA Type II slot	• 2 button PS/2 TouchPad
I/O Devices		• 2 button PS/2 TouchPad
	• 4 in 1 card reader slot support MS/MS Pro./SD/MMC card	
	• Smart Card reader	O 10 ' HDML , (HDT), D ' ,
I/O Ports	• Four USB 2.0 ports	One 19 pin HDMI connector for HDTV or Projector
	One Head Phone out phone jack	One 9 pin D-sub Serial port
	 One Mic-in phone jack for external Microphone 	One15 pin D-sub VGA port for ext. monitor/projector
	One RJ-45 jack for internal 10/100/1000Mbps Ethernet	 One optional ext. antenna connector for GPS
	• One DC-In jack	·
Keyboard	One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illum	·
Keyboard	One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illum Function Keys:	ninated keyboard)
Keyboard	 One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illun Function Keys: Fn+F1: Bluetooth on/off 	ninated keyboard) • Fn+F7: Brightness Increase
Keyboard	One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illum Function Keys:	ninated keyboard)
Keyboard	 One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illun Function Keys: Fn+F1: Bluetooth on/off 	ninated keyboard) • Fn+F7: Brightness Increase
Keyboard	 One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illun Function Keys: Fn+F1: Bluetooth on/off Fn+F2: 3G on/off 	ninated keyboard) • Fn+F7: Brightness Increase • Fn+F8: Volume Decrease
Keyboard	 One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illum Function Keys: Fn+F1: Bluetooth on/off Fn+F2: 3G on/off Fn+F3: Touchpad on/off 	ninated keyboard) • Fn+F7: Brightness Increase • Fn+F8: Volume Decrease • Fn+F9: Volume Increase
Keyboard	 One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illum Function Keys: Fn+F1: Bluetooth on/off Fn+F2: 3G on/off Fn+F3: Touchpad on/off Fn+F4: Suspend to RAM/Suspend to HDD 	ninated keyboard) • Fn+F7: Brightness Increase • Fn+F8: Volume Decrease • Fn+F9: Volume Increase • Fn+F10: Mute
Keyboard Wireless/Communications	 One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illun Function Keys: Fn+F1: Bluetooth on/off Fn+F2: 3G on/off Fn+F3: Touchpad on/off Fn+F4: Suspend to RAM/Suspend to HDD Fn+F5: LCD/Ext. Display Switch(LCD->Ext. Display->Both) 	ninated keyboard) • Fn+F7: Brightness Increase • Fn+F8: Volume Decrease • Fn+F9: Volume Increase • Fn+F10: Mute
	 One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illum Function Keys: Fn+F1: Bluetooth on/off Fn+F2: 3G on/off Fn+F3: Touchpad on/off Fn+F4: Suspend to RAM/Suspend to HDD Fn+F5: LCD/Ext. Display Switch(LCD->Ext. Display->Both) Fn+F6: Brightness Decrease Integrated 56 Kbps v.92 fax/modem (MDC module) 	ninated keyboard) • Fn+F7: Brightness Increase • Fn+F8: Volume Decrease • Fn+F9: Volume Increase • Fn+F10: Mute • Fn+F11: Touch panel on/off • Bluetooth 2.1+EDR (option)
	 One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illum Function Keys: Fn+F1: Bluetooth on/off Fn+F2: 3G on/off Fn+F3: Touchpad on/off Fn+F4: Suspend to RAM/Suspend to HDD Fn+F5: LCD/Ext. Display Switch(LCD->Ext. Display->Both) Fn+F6: Brightness Decrease 	ninated keyboard) • Fn+F7: Brightness Increase • Fn+F8: Volume Decrease • Fn+F9: Volume Increase • Fn+F10: Mute • Fn+F11: Touch panel on/off • Bluetooth 2.1+EDR (option) • Intel Mini Express Card Wireless LAN (802.11a/b/n)
Wireless/Communications	One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illum Function Keys: Fn+F1: Bluetooth on/off Fn+F2: 3G on/off Fn+F3: Touchpad on/off Fn+F4: Suspend to RAM/Suspend to HDD Fn+F5: LCD/Ext. Display Switch(LCD->Ext. Display->Both) Fn+F6: Brightness Decrease Integrated 56 Kbps v.92 fax/modem (MDC module) Integrated 10/100/1000 Mbps Ethernet (RJ-45 connector) Internal 2nd Mini PCI Express slot to support either WWAN/3	ninated keyboard) • Fn+F7: Brightness Increase • Fn+F8: Volume Decrease • Fn+F9: Volume Increase • Fn+F10: Mute • Fn+F11: Touch panel on/off • Bluetooth 2.1+EDR (option) • Intel Mini Express Card Wireless LAN (802.11a/b/n)
	One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illum Function Keys: Fn+F1: Bluetooth on/off Fn+F2: 3G on/off Fn+F3: Touchpad on/off Fn+F4: Suspend to RAM/Suspend to HDD Fn+F5: LCD/Ext. Display Switch(LCD->Ext. Display->Both) Fn+F6: Brightness Decrease Integrated 56 Kbps v.92 fax/modem (MDC module) Integrated 10/100/1000 Mbps Ethernet (RJ-45 connector) Internal 2nd Mini PCI Express slot to support either WWAN/3 BIOS administrator password / Boot password	ninated keyboard) • Fn+F7: Brightness Increase • Fn+F8: Volume Decrease • Fn+F9: Volume Increase • Fn+F10: Mute • Fn+F11: Touch panel on/off • Bluetooth 2.1+EDR (option) • Intel Mini Express Card Wireless LAN (802.11a/b/n) 3G or WiMAX or GPS • Smart Card reader
Wireless/Communications	One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illum Function Keys: Fn+F1: Bluetooth on/off Fn+F2: 3G on/off Fn+F3: Touchpad on/off Fn+F4: Suspend to RAM/Suspend to HDD Fn+F5: LCD/Ext. Display Switch(LCD->Ext. Display->Both) Fn+F6: Brightness Decrease Integrated 56 Kbps v.92 fax/modem (MDC module) Integrated 10/100/1000 Mbps Ethernet (RJ-45 connector) Internal 2nd Mini PCI Express slot to support either WWAN/3	ninated keyboard) • Fn+F7: Brightness Increase • Fn+F8: Volume Decrease • Fn+F9: Volume Increase • Fn+F10: Mute • Fn+F11: Touch panel on/off • Bluetooth 2.1+EDR (option) • Intel Mini Express Card Wireless LAN (802.11a/b/n) 3G or WiMAX or GPS
Wireless/Communications Security	One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illum Function Keys: Fn+F1: Bluetooth on/off Fn+F2: 3G on/off Fn+F3: Touchpad on/off Fn+F4: Suspend to RAM/Suspend to HDD Fn+F5: LCD/Ext. Display Switch(LCD->Ext. Display->Both) Fn+F6: Brightness Decrease Integrated 56 Kbps v.92 fax/modem (MDC module) Integrated 10/100/1000 Mbps Ethernet (RJ-45 connector) Internal 2nd Mini PCI Express slot to support either WWAN/3 BIOS administrator password / Boot password Fingerprint Scanner	ninated keyboard) • Fn+F7: Brightness Increase • Fn+F8: Volume Decrease • Fn+F9: Volume Increase • Fn+F10: Mute • Fn+F11: Touch panel on/off • Bluetooth 2.1+EDR (option) • Intel Mini Express Card Wireless LAN (802.11a/b/n) 3G or WiMAX or GPS • Smart Card reader
Wireless/Communications Security AC/ DC Adapter	One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illum Function Keys: Fn+F1: Bluetooth on/off Fn+F2: 3G on/off Fn+F3: Touchpad on/off Fn+F4: Suspend to RAM/Suspend to HDD Fn+F5: LCD/Ext. Display Switch(LCD->Ext. Display->Both) Fn+F6: Brightness Decrease Integrated 56 Kbps v.92 fax/modem (MDC module) Integrated 10/100/1000 Mbps Ethernet (RJ-45 connector) Internal 2nd Mini PCI Express slot to support either WWAN/3 BIOS administrator password / Boot password Fingerprint Scanner TPM 1.2	ninated keyboard) • Fn+F7: Brightness Increase • Fn+F8: Volume Decrease • Fn+F9: Volume Increase • Fn+F10: Mute • Fn+F11: Touch panel on/off • Bluetooth 2.1+EDR (option) • Intel Mini Express Card Wireless LAN (802.11a/b/n) 3G or WiMAX or GPS • Smart Card reader
Wireless/Communications Security	One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illun Function Keys: Fn+F1: Bluetooth on/off Fn+F2: 3G on/off Fn+F3: Touchpad on/off Fn+F4: Suspend to RAM/Suspend to HDD Fn+F5: LCD/Ext. Display Switch(LCD->Ext. Display->Both) Fn+F6: Brightness Decrease Integrated 56 Kbps v.92 fax/modem (MDC module) Integrated 10/100/1000 Mbps Ethernet (RJ-45 connector) Internal 2nd Mini PCI Express slot to support either WWAN/3 BIOS administrator password / Boot password Fingerprint Scanner TPM 1.2 Input: AC 100~240V 50/60Hz, Output: DC 20V/3.25A/65W Standard: 6 cell 4400mAh Li-Ion battery (Approx. 5 hrs*)	ninated keyboard) • Fn+F7: Brightness Increase • Fn+F8: Volume Decrease • Fn+F9: Volume Increase • Fn+F10: Mute • Fn+F11: Touch panel on/off • Bluetooth 2.1+EDR (option) • Intel Mini Express Card Wireless LAN (802.11a/b/n) 3G or WiMAX or GPS • Smart Card reader
Wireless/Communications Security AC/ DC Adapter Battery	One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illum Function Keys: Fn+F1: Bluetooth on/off Fn+F2: 3G on/off Fn+F3: Touchpad on/off Fn+F4: Suspend to RAM/Suspend to HDD Fn+F5: LCD/Ext. Display Switch(LCD->Ext. Display->Both) Fn+F6: Brightness Decrease Integrated 56 Kbps v.92 fax/modem (MDC module) Integrated 10/100/1000 Mbps Ethernet (RJ-45 connector) Internal 2nd Mini PCI Express slot to support either WWAN/3 BIOS administrator password / Boot password Fingerprint Scanner TPM 1.2 Input: AC 100~240V 50/60Hz, Output: DC 20V/3.25A/65W Standard: 6 cell 4400mAh Li-Ion battery (Approx. 5 hrs*) Optional: 9 cell 6600mAh Li-Ion battery (Approx. 8 hrs*)	ninated keyboard) • Fn+F7: Brightness Increase • Fn+F8: Volume Decrease • Fn+F9: Volume Increase • Fn+F10: Mute • Fn+F11: Touch panel on/off • Bluetooth 2.1+EDR (option) • Intel Mini Express Card Wireless LAN (802.11a/b/n) 3G or WiMAX or GPS • Smart Card reader • Kensington Lock
Wireless/Communications Security AC/ DC Adapter	 One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illun Function Keys: Fn+F1: Bluetooth on/off Fn+F2: 3G on/off Fn+F3: Touchpad on/off Fn+F4: Suspend to RAM/Suspend to HDD Fn+F5: LCD/Ext. Display Switch(LCD->Ext. Display->Both) Fn+F6: Brightness Decrease Integrated 56 Kbps v.92 fax/modem (MDC module) Integrated 10/100/1000 Mbps Ethernet (RJ-45 connector) Internal 2nd Mini PCI Express slot to support either WWAN/3 BIOS administrator password / Boot password Fingerprint Scanner TPM 1.2 Input: AC 100~240V 50/60Hz, Output: DC 20V/3.25A/65W Standard: 6 cell 4400mAh Li-Ion battery (Approx. 5 hrs*) Optional: 9 cell 6600mAh Li-Ion battery (Approx. 8 hrs*) 352mm (W) x 256mm (D) x 37-41 mm (H) / 13.8" (W) x 10" (D) x 	ninated keyboard) • Fn+F7: Brightness Increase • Fn+F8: Volume Decrease • Fn+F9: Volume Increase • Fn+F10: Mute • Fn+F11: Touch panel on/off • Bluetooth 2.1+EDR (option) • Intel Mini Express Card Wireless LAN (802.11a/b/n) 3G or WiMAX or GPS • Smart Card reader • Kensington Lock
Wireless/Communications Security AC/ DC Adapter Battery	One DC-In jack Spill resistant keyboard (88 Keys with Windows logo), LED illum Function Keys: Fn+F1: Bluetooth on/off Fn+F2: 3G on/off Fn+F3: Touchpad on/off Fn+F4: Suspend to RAM/Suspend to HDD Fn+F5: LCD/Ext. Display Switch(LCD->Ext. Display->Both) Fn+F6: Brightness Decrease Integrated 56 Kbps v.92 fax/modem (MDC module) Integrated 10/100/1000 Mbps Ethernet (RJ-45 connector) Internal 2nd Mini PCI Express slot to support either WWAN/3 BIOS administrator password / Boot password Fingerprint Scanner TPM 1.2 Input: AC 100~240V 50/60Hz, Output: DC 20V/3.25A/65W Standard: 6 cell 4400mAh Li-Ion battery (Approx. 5 hrs*) Optional: 9 cell 6600mAh Li-Ion battery (Approx. 8 hrs*)	ninated keyboard) • Fn+F7: Brightness Increase • Fn+F8: Volume Decrease • Fn+F9: Volume Increase • Fn+F10: Mute • Fn+F11: Touch panel on/off • Bluetooth 2.1+EDR (option) • Intel Mini Express Card Wireless LAN (802.11a/b/n) 3G or WiMAX or GPS • Smart Card reader • Kensington Lock

A certified 8(a), SDB, DBE, SBE, MBE, WBE firm. DuraTech USA Inc.

6765 Westminster Ave #314 Westminster, CA 92683

Phone: (714) 898-2171 Fax: 866-704-9132

Email: sales@DuraTechUSA.com www.DuraTechUSA.com

<sup>The specification and pictures are subject to change without notice.
All brand names are registered trademarks of their respective owners.
Battery life may vary based on setting and usage.</sup>